

**Question 18 (5 marks)**

**Resistor Colour Code Chart**

<i>Colour</i>	<i>Value</i>	<i>Multiplying factor</i>	<i>Tolerance</i>
Black	0	1	–
Brown	1	10	1%
Red	2	100	2%
Orange	3	1 000	–
Yellow	4	10 000	–
Green	5	100 000	0.5%
Blue	6	1 000 000	0.25%
Violet	7	–	0.1%
Grey	8	–	–
White	9	–	–
Gold	–	0.1	5%
Silver	–	0.01	10%

- (a) Use the Resistor Colour Code Chart to find the colour code of the resistor. 2

<i>Value</i>	<i>Tolerance</i>	<i>Band 1</i>	<i>Band 2</i>	<i>Band 3</i>	<i>Band 4</i>
680	1%	Blue	Grey	Black	Brown

- (b) Determine the maximum value of the following resistor, showing all working. 3

<i>Band 1</i>	<i>Band 2</i>	<i>Band 3</i>	<i>Band 4</i>
Red	Black	Blue	Gold

*Band*                      |    1    2    3    4  
 -----  
2    0    10<sup>6</sup>    5%
 Max value is 20 000 000 ± 5%  
 -----  
 -----  
 -----